

3-PHASE CONNECTION DIAGRAM

CONTROL TERMINAL STRIP

R	S	E	U	V	12	E	1	2	L1/M1	L2/M2	M3
1	2	3	4	5	6	7	8	9	10	11	12
L1	L2	GND	U	V	12	E	1	2	L1	L2	L3

Wiring Instructions

1. Connect inbound L1, L2, and L3 to terminals 10, 11, and 12 (all bottom).
2. Connect inbound Ground to terminal 3 (bottom).
3. Run jumper wire from terminal 10 (top) to 1 (bottom).
4. Run jumper wire from terminal 11(top) to 2 (bottom).
5. Connect pumpmotor leads M1, M2, and M3 to terminals 10, 11, and 12 (all top).
6. Connect pumpmotor ground to terminal 3 (bottom)

NOTE: Should the pumpmotor run in the reverse direction, swap two of the three inbound leads. (Will not effect performance of other components.)

